

Essential II DIGITAL

„Best Buy“ turntable with MM pre-amp + OPTICAL OUTPUT

- Ideal for connection to multiroom systems (SONOS, HEOS etc) or TVs, soundbars and portable audio
- Perfect solution if only a digital input is available
- Easy set-up
- Belt drive with silicone belt and low vibration motor
- 8,6" aluminium tonearm with sapphire bearings
- Ortofon OM5e cartridge pre-mounted
- Built-in phono pre-amplifier with analogue & digital out
- Gold-plated RCA interconnect cable included
- Special turntable feet for effective decoupling
- High-gloss colour options: Black, White, Red

Speed	33, 45 (manual speed change)
Principle	belt drive
Speed variance	33: 0,80% 45: 0,70%
Wow & flutter	33: 0,29% 45: 0,27%
Platter	300mm particle board & felt mat (0,8kg)
Main bearing	stainless steel
Tonearm	8,6" aluminium
Effective arm length	218,5 mm
Overhang	22,0mm
Effective tonearm mass	8,0gr
Counterweight for mass	3 - 5,5g (included)
Tracking force range	0 - 25mN (OM5 18mN recommended)
Line output voltage typically	160mV/1kHz at 4mV/1kHz input
Noise floor	>73dB
RIAA-equalisation accuracy	20Hz-20kHz / max. 0,5dB
Optical output	24/96 kHz (bit depth/sampling frequency)
Included accessory	power supply, dust cover
Power consumption	4,5 watts
Dimensions	420 x 112 x 330mm (WxHxD)
Weight	4,0 kg net



Turntable innovation with DIGITAL OPTIC and line output!

Many new audio systems, like home cinema receivers, soundbars, multiroom audio, TVs and Bluetooth speakers only offer digital optic input connections: So up to now vinyl lovers using such systems had no chance to play their records on those systems. **The perfect solution is: Essential II DIGITAL**

An unique belt-drive turntable with built-in MM pre-amplifier that features **digital optic** as well as **analogue** amplifier connection options. Delivered with acrylic lid and with black, white and red high-gloss colour options.

